

## DAC30

### DAC30 IR commands

Tomas Andersson  
2013-08-27

**RC5 Address**            **Hex Address**  
13                            0x0d

Command	Value	Hex Value	Description
Toggle standby	12	0x0c	Standby on/off toggle
Standby	1	0x01	Only standby
Operate	2	0x02	Only operate
Arrow up	19	0x13	Input / menu up
Arrow down	25	0x19	Input / menu down
Dim	10	0x0a	Dim level toggle
Num 1	8	0x08	Select input 1, select menu item 1
Num 2	9	0x09	Select input 2, select menu item 2
Num 3	11	0x0b	Select input 3, select menu item 3
Num 4	13	0x0d	Select input 4, select menu item 4
Num 5	14	0x0e	Select input PC, select menu item 5
Num 6	15	0x0f	Select input MEDIA, select menu item 6
Num 7	16	0x10	Select menu item 7
Num 8	17	0x11	Select menu item 8